


**Technical requirements for electronic control gears for LED and fluorescent luminaires (dimmable or non-dimmable) for operation on INOTEC central battery systems (CPS 220 / CPS FUSION) and emergency power supply systems (NEA)**

**- General requirements -**

Manufacturer: OSRAM GmbH Marcel-Breuer-Str. 6 D-80807 München	Type / Description: Luminaire EVG: OTi DALI 50/220-240/1A4 LT2 L G2 AN00954 LED:
Project / Place / Project ID:	Specified by: Name: R.Brazinskas Company: OSRAM GmbH Date: 20.08.2019

Features	Techn. data / INOTEC requirements	Explanation	Fullfilled (Yes / No)
1 Voltage range AC	230V ± 10%	Voltage range in normal mains operation	Yes
2 Voltage range DC	186V - 260V	Possible voltage range in emergency operation	Yes
3 Control gear suitable for "Joker-Voltage" ?	B2-rectification of the AC voltage (without smoothing)	Pulsating DC voltage 	Yes
4 Control gear compatible with change-over time of the system?	Change-over time: 150 - 1000ms	Typical change-over time of INOTEC systems between mains- and battery operation	Yes
5 Starting behavior of the control gear in AC and DC operation	Stable current consumption within 1.6s	Necessary for individual lamp monitoring (SV). The nominal current of the control gear must be reached within this time if the lamp is intact or defective.	Yes
6 Control gear complies with the standard: (only for fluorescent lamps)	DIN EN 60929	AC and/or DC-supplied electronic control gear for tubular fluorescent lamps - Performance requirements	Not relevant
7 Control gear complies with the standard: (only for fluorescent lamps)	DIN EN 61347-2-3 (incl. Attachment J)	Particular requirements for AC and/or DC supplied electronic control gear for fluorescent lamps	Not relevant
8 Control gear complies with the standard: (only for LED)	DIN EN 62384	DC or AC supplied electronic control gear for LED modules - Performance requirements	Yes
9 Control gear complies with the standard: (only for LED)	DIN EN 61347-2-13	Lamp control gear - Part 2-13: Particular requirements for DC or AC supplied electronic control gear for LED modules	Yes
10 Control gear complies with the standard:	DIN EN 55015 (Measurement on AC and DC)	Limits and methods of measurement of radio interference	Yes
11 Control gear complies with the standard:	DIN EN 61000-3-2	Electromagnetic compatibility (EMC) - Part 3-2: Limits - Limits for harmonic current emissions (equipment input current ≤ 16 A per phase)	Yes
12 Control gear complies with the standard:	DIN EN 61547	Equipment for general lighting purposes — EMC immunity requirements	Yes
13 Control gear complies with the DALI-standards:	DIN EN 62386-101 /-102 / -207 *1	The control and status information for monitoring the luminaire is provided via DALI commands. The DALI commands must be 100% compatible.	Yes

Note: VDE 0108 is not a standard for ECG, marking is not applicable

Technical requirements for electronic control gears for LED and fluorescent luminaires (dimmable or non-dimmable) for operation on INOTEC central battery systems (CPS 220 / CPS FUSION) and emergency power supply systems (NEA)



**- Technical specifications -**

Manufacturer: OSRAM GmbH Marcel-Breuer-Str. 6 D-80807 München	Type / Description: Luminaire
	EVG: OTi DALI 50/220-240/1A4 LT2 L G2 AN00954
	LED:
Project / Place / Project ID:	Specified by:
	Name: R.Brazinskas
	Company: OSRAM GmbH
	Date: 20.08.2019

Features	Explanation	Manufacturer information
14 Nominal current of the control gear with connected illuminant in <b>AC- operation (230V)</b>	Selection guide for the calculation of the max. number of luminaires per circuit	Table 1 mA
15 Nominal current of the control gear with connected illuminant in <b>DC- operation (186V / 216V / 240V)</b>	Selection guide for the calculation of the necessary battery capacity and selection guide for determination of the monitoring module to recognise a normal working lamp correctly. <b>Note:</b> If a dimming level is activated for a dimmable control gear, the rated currents must be specified for the set dimming level.	Table 1 mA (186V)
		Table 1 mA (216V)
		Table 1 mA (240V)
16 Current consumption of the control gear <b>without</b> or with <b>defective</b> illuminant in <b>DC- operation (186V and 240V)</b>	Selection guide for determination of the monitoring module to recognise a lamp failure correctly.	Table 1 mA (186V)
		Table 1 mA (240V)
17 Dimming level in emergency mode (DC or "Joker") (for dimmable control gear, if activated)	Important for the safety lighting design	15 %
18 DC detection <b>completely</b> deactivable ? (for dimmable control gear)	To ensure correct operation, the control gear should not react to a change of the input voltage (DC or "Joker"). In this case, the INOTEC DALI module (DALI-SV module or FMD 230/DALI) controls the control gear.	Yes
19 Max. inrush current of the control gear with connected illuminant in <b>AC- operation (230V)</b>	Important for determining the maximum permissible number of luminaires per circuit in order to take account of the maximum contact load capacity of the circuit changeover circuit or monitoring module.	20 / 216 A / $\mu$ s
20 Use of DALI commands according to IEC 62386 part 102: - DPAC (level) - RECALL MAX LEVEL 0x05 - RECALL MIN LEVEL 0x06 - QUERY STATUS 0x90 - QUERY ACTUAL LEVEL 0xA0 - QUERY LAMP FAILURE 0x92	Control and status information for monitoring the luminaires: - Direct setting of a dimming value - Set maximum level - Set minimum level - Requests status telegram - Requests current dimming value - Requests lamp failure status ( <b>after 2 / 2.5 / 3 seconds!</b> )	Yes
Luminaires, which should work as emergency lighting, have to be in accordance with DIN EN 60598-2-22. (Particular requirements - Luminaires for emergency lighting).		

Notes:

See notes listed in Annex

For the correctness:

Garching, 20.08.2019

Place, Date

  
Martin Hatz  
DI DS D EM

Signature

  
Bernhard Schemmel  
DI DS QM L SC EM

## Notes

- 1: Communication between DALI-SV-Module and DALI LED driver is 100% done via DALI-commands according to IEC 62386-101 /-102 so the DALI LED driver must sign with the DALI logo
- 2: The DC Output Level is locked in DC Mode to 15% as preset factory setting.  
This preset value ( luminous flux in case of DC-voltage) can be adjusted project depending via DALI Magic and T4 Tronic.  
To enable the adjustment of the luminous flux via the V-CG-SB.1, the DC detection has to be deactivated via T4T.
3. Not to be used in high risk areas, special release required
4. For calculation the inrush current of the monitoring module must be considered!

<b>Manufacturer:</b> OSRAM GmbH Marcel-Breuer Str. 6 D-80807 München	<b>Product:</b>  <b>OTI DALI 50/220-240/1A4 LT2 L G2</b> <b>( AN00954 )</b>	<b>OSRAM GmbH</b>
---	--	-------------------

Table 1

	AC-operation		DC-Operation			
	AC-operation @ 230V ( mA )	AC-operation @ 240V ( mA )	186V ( mA )	216V ( mA )	240V ( mA )	260V ( mA )
<b>Values for load range</b>						
Maximum Load /mA	224	215	55	46	43	40
U <sub>out</sub> = I <sub>out</sub> = P=						
Short Load	34	34	< 15	< 15	< 15	< 15
Open Load	34	34	< 15	< 15	< 15	< 15