

**Technical requirements for electronic control gears for LED and fluorescent luminaires (dimmable or non-dimmable) for operation on INOTEC central battery systems (CPS 220 / CPS FUSION) and emergency power supply systems (NEA)**

**- General requirements -**

Manufacturer:	Type / Description:
	Luminaire
	EVG:
Project / Place / Project ID:	LED:
	Specified by:
	Name:
	Company:
	Date:

Features	Techn. data / INOTEC requirements	Explanation	Fulfilled (Yes / No)
1 Voltage range AC	230V ± 10%	Voltage range in normal mains operation	
2 Voltage range DC	186V - 260V	Possible voltage range in emergency operation	
3 Control gear suitable for "Joker-Voltage" ?	<b>B2-rectification of the AC voltage (without smoothing)</b>	Pulsating DC voltage 	
4 Control gear compatible with change-over time of the system?	<b>Change-over time: 150 - 1000ms</b>	Typical change-over time of INOTEC systems between mains- and battery operation	
5 Starting behavior of the control gear in AC and DC operation	<b>Stable current consumption within 1.6s</b>	Necessary for individual lamp monitoring (SV). The nominal current of the control gear must be reached within this time if the lamp is intact or defective.	
6 Control gear complies with the standard: (only for fluorescent lamps)	<b>DIN EN 60929</b>	AC and/or DC-supplied electronic control gear for tubular fluorescent lamps - Performance requirements	
7 Control gear complies with the standard: (only for fluorescent lamps)	<b>DIN EN 61347-2-3 (incl. Attachment J)</b>	Particular requirements for AC and/or DC supplied electronic control gear for fluorescent lamps	
8 Control gear complies with the standard: (only for LED)	<b>DIN EN 62384</b>	DC or AC supplied electronic control gear for LED modules - Performance requirements	
9 Control gear complies with the standard: (only for LED)	<b>DIN EN 61347-2-13</b>	Lamp control gear - Part 2-13: Particular requirements for DC or AC supplied electronic control gear for LED modules	
10 Control gear complies with the standard:	<b>DIN EN 55015 (Measurement on AC and DC)</b>	Limits and methods of measurement of radio interference	
11 Control gear complies with the standard:	<b>DIN EN 61000-3-2</b>	Electromagnetic compatibility (EMC) - Part 3-2: Limits - Limits for harmonic current emissions (equipment input current ≤ 16 A per phase)	
12 Control gear complies with the standard:	<b>DIN EN 61547</b>	Equipment for general lighting purposes — EMC immunity requirements	
13 Control gear complies with the DALI-standards:	<b>DIN EN 62386-101 /-102 / -207</b>	The control and status information for monitoring the luminaire is provided via DALI commands. The DALI commands must be 100% compatible.	

Note: VDE 0108 is not a standard for ECG, marking is not applicable

**Technical requirements for electronic control gears for LED and fluorescent luminaires (dimmable or non-dimmable) for operation on INOTEC central battery systems (CPS 220 / CPS FUSION) and emergency power supply systems (NEA)**



**- Technical specifications -**

Manufacturer:	Type / Description:
	Luminaire
	EVG:
Project / Place / Project ID:	LED:
	Specified by:
	Name:
	Company:
	Date:

Features		Explanation	Manufacturer spec.
14	Nominal current of the control gear with connected illuminant in <b>AC- operation (230V)</b>	Selection guide for the calculation of the max. number of luminaires per circuit	mA
15	Nominal current of the control gear with connected illuminant in <b>DC- operation (186V / 216V / 240V)</b>	Selection guide for the calculation of the necessary battery capacity and selection guide for determination of the monitoring module to recognise a normal working lamp correctly.	mA (186V)
			mA (216V)
			mA (240V)
16	Nominal current of the control gear with connected illuminant <b>at set dimming level in DC-operation (186V / 216V / 240V)</b> (for dimmable control gear)	Selection guide for determination of the monitoring module to recognise a normal working lamp correctly.	mA (186V)
			mA (216V)
			mA (240V)
17	Current consumption of the control gear <b>without</b> or with <b>defective</b> illuminant in <b>DC- operation (186V and 240V)</b>	Selection guide for determination of the monitoring module to recognise a lamp failure correctly.	mA (186V)
			mA (240V)
18	Current consumption of the control gear <b>without</b> or with <b>defective</b> illuminant in <b>AC- operation (230V)</b>	Selection guide for determination of the monitoring module to recognise a lamp failure correctly.	mA
19	Dimming level in emergency mode (DC or "Joker") (for dimmable control gear, if activated)	Important for the safety lighting design	%
20	DC detection <b>completely</b> deactivatable ? (for dimmable control gear)	To ensure correct operation, the control gear should not react to a change of the input voltage (DC or "Joker"). In this case, the INOTEC DALI module (DALI-SV module or FMD 230/DALI) controls the control gear.	
21	Max. inrush current of the control gear with connected illuminant in <b>AC- operation (230V)</b>	Important for determining the maximum permissible number of luminaires per circuit in order to take account of the maximum contact load capacity of the circuit changeover circuit or monitoring module.	A / $\mu$ s
22	Use of DALI commands according to IEC 62386 part 102: - DPAC (level) - RECALL MAX LEVEL 0x05 - RECALL MIN LEVEL 0x06 - QUERY STATUS 0x90 - QUERY ACTUAL LEVEL 0xA0 - QUERY LAMP FAILURE 0x92	Control and status information for monitoring the luminaires: - Direct setting of a dimming value - Set maximum level - Set minimum level - Requests status telegram - Requests current dimming value - Requests lamp failure status ( <b>after 2 / 2.5 / 3 seconds!</b> )	

Luminaires, which should work as emergency lighting, have to be in accordance with DIN EN 60598-2-22. (Particular requirements - Luminaires for emergency lighting).

Notes:

For the correctness:

[Redacted signature area]

Place, Date

Martin Hutzl  
OSRAM DI DS EMA ITM PC - GER2

Signature