

Requirements for dimmable DALI control gears for fluorescent lamps and LED			Version 5
Manufacturer: OSRAM GmbH Marcel-Breuer-Str. 6 D-80807 München	Type / description: ECG-type: OTi DALI 35/220-240/1A0 NFC TW (4062172123501) Date: 12.01.2023		Manufacturer information Complies: YES/NO
Features:	CEAG data:	Explanation:	
Control gear suitable for a DC voltage range:	186V - 260V DC (for Lead-Battery)	Possible voltage range of the battery in emergency mode. (Not for AT-S* Systems required)	Yes
Control gear compatible with the switch-over time of the system?	Switch-over time: 180 ms - 450 ms	Typical switch-over time of CEAG systems between mains supply and emergency power supply	No
Starting behavior of the control gear:	Stable current consumption after less than 1.6 sec. maximum.	A stable operation of the control gear after 1.6 seconds of start up is required for the right functionality of the individual monitoring. With max. 20 luminaires for one current circuit: ΔI in sum < 250 mA are allowed	Yes
Control gear compatible with CEAG STAR-Technology:	Phase-cut telegram (PAT): max. 30 phases (half waves) with max. 60° phase-cuts	During the CEAG STAR switching process, up to 30 half-waves are cut at a maximum of 60°. The control gear must not exhibit any malfunctions such as switching off, flickering	Yes
<u>only for fluorescent lamps:</u> Control gear complies with the standard:	DIN EN 60929	AC and/or DC-supplied electronic control gear for tubular fluorescent lamps - Performance requirements	Not relevant
<u>only for fluorescent lamps:</u> Control gear complies with the standard:	DIN EN 61347-2-3 (incl. Attachment J)	Particular requirements for AC and/or DC supplied electronic control gear for fluorescent lamps	Not relevant
<u>only for LED:</u> Control gear complies with the standard:	DIN EN 62384	DC. Or AC supplied electronic control gear for LED modules - Performance requirements	Yes
<u>only for LED:</u> Control gear complies with the standard:	DIN EN 61347-2-13	Lamp controlgear — Part 2-13: Particular requirements for d. c. or a. c. supplied electronic controlgear for LED modules	Yes
Fullfilled the standard:	DIN EN 55015 (Measurement on AC And DC)	Limits and methods of measurement of radio disturbance characteristics of electrical lighting and similar equipment	Yes
Fullfilled the standard:	DIN EN 61547	Equipment for general lighting purposes — EMC immunity requirements	(*2) YES
Fullfilled the DALI standards:	DIN EN 62386-101 /-102 / -207*	Control gear must have the DALI Logo*	Yes
Note: VDE 0108 is not a standard for ECG, marking is not applicable			
Features:	CEAG-Data:	Explanation:	Manufacturer information:
<u>Important for function test!</u> According to IEC 62386 Part 102 Support of : DALI command 145 (Query Control Gear) DALI command 146 (Query Lamp Failure)	According to IEC 62386 Part 102	To detect a lamp failure, the V-CG-SB.1 module send DALI command queries (145/146) to the DALI LED driver. These DALI commands are necessary to ensure the lamp failure detection, and must be support by the control gear.	Yes
<u>Important for DC operation:</u> DALI light level	In case of locked DALI light level in DC operation (EOF=Emergency Output Level), the V-CG-SB.1 can not change the light level !	In DC-emergency case the DALI-Light Level is locked to prevent unwanted changes of the luminous flux.	Locked
<u>Important for lighting design:</u> If DALI-Light level is locked, the value of the preset DC-Lightlevel (in %) is required		Pre-set DC-Light Level e.g. 15% (DALI-value 185 for logarithmic dimming curve)	(*1) 15%
Note: Important for the planning - Max. no. Of luminaires per circuit			
<u>Important for the contact load SKU:</u> Max. inrush current each converter/luminaire in AC-operation:	Max. permitted inrush current per circuit: SKU 2 x 3A (CG) => 120 A SKU 1 x 6A (CG) => 180 A SKU 4 x 1,5A CG-S => 60 A SKU 2 x 3A CG-S => 250 A SKU 1 x 6A CG-S => 250 A SOU CG-S // S* => 250 A SU S* => 250 A	19A/200 µs (measured at 50 % Ipeak) per pcs. The declaration of the inrush current of the luminaire is important, to calculate the max. possible luminaires on one circuit, to consider the max. contact load limitation of the circuit.	
Luminaires, which are used for emergency lighting, must be according to the standard DIN EN 60598-2-22 (particular requirements - Luminaires for emergency lighting)			
*Control of V-CG-SB.1 to the DALI LED driver is 100% done via DALI-commands according to IEC 62386-101 /-102 so the DALI LED driver must sign with the DALI logo			
*1: The DC Output Level is locked in DC Mode to 15% as preset factory setting. This preset value (luminous flux in case of DC-voltage) can be adjusted project depending via DALI Magic and T4 Tronic. To enable the adjustment of the luminous flux via the V-CG-SB.1, the DC detection has to be deactivated via T4T.			
*2: Not to be used in high risk areas, special release required.			
Max. one DALI- Driver to wire with one EL-monitoring module Max. 1 DALI- Driver to wire with 1 V-CG-SB.1			
In use of manifold ballasts, the different lamp failure detection of the manufacturer must be consider! Some devices don't detect a failure if one lamp is defect.			

Manufacturer: OSRAM GmbH Marcel-Breuer Str. 6 D-80807 München	Product: OTi DALI 35_220-240_1A0_NFC_TW (AM42975)	OSRAM GmbH
--	--	-------------------

Table 1

Values for load range	AC-operation				DC-Operation (For DALI Devices @ default DC Dim level e.g. 15%)			
	189VAC/50Hz I _{rms_in} (mA)	230VAC/50Hz I _{rms_in} (mA)	240VAC/50Hz I _{rms_in} (mA)	264VAC/50Hz I _{rms_in} (mA)	186VDC I _{dc_in} (mA)	216VDC I _{dc_in} (mA)	240VDC I _{dc_in} (mA)	260VDC I _{dc_in} (mA)
Min. Load /mA P _{out} =9.94W	not supported (83.6)	76,3	75,3	73,8	21,4	18,8	17,5	15,5
	PF: 0.828	PF: 0.752	PF: 0.733	PF: 0.690	PF: NA	PF: NA	PF: NA	PF: NA
Mid. Load /mA P _{out} =21.2W	not supported (148)	126,7	123,0	116,0	29,9	26,1	24,0	22,8
	PF: 0.932	PF: 0.893	PF: 0.881	PF: 0.853	PF: NA	PF: NA	PF: NA	PF: NA
Max. Load /mA P _{out} =36.9W	not supported (230)	196,9	189,5	175,5	43,5	37,6	34,3	32,3
	PF: 0.966	PF: 0.947	PF: 0.941	PF: 0.924	PF: NA	PF: NA	PF: NA	PF: NA
Short/Open Load	not supported (36.8)	40,4	42,4	45,5	0,1	0,1	0,1	0,1
	PF: 0.004	PF: 0.013	PF: 0.014	PF: 0.015	PF: NA	PF: NA	PF: NA	PF: NA

Remarks:

- 1.) This table shows the currents consumption of the driver at three different operating points (P_{max}, P_{mid}, P_{min}) for AC and DC operation.
- 2.) This table is intended for rough design decisions . It is not a replacement for individual functional measurements!