

**Technical requirements for electronic control gears for LED and fluorescent luminaires (dimmable or non-dimmable) for operation on INOTEC central battery systems (CPS 220 / CPS FUSION) and emergency power supply systems (NEA)**

**- General requirements -**

Manufacturer:	Type / Description:
	Luminaire
	EVG:
Project / Place / Project ID:	LED:
	Specified by:
	Name:
	Company:
	Date:

Features	Techn. data / INOTEC requirements	Explanation	Fulfilled (Yes / No)
1 Voltage range AC	230V ± 10%	Voltage range in normal mains operation	
2 Voltage range DC	186V - 260V	Possible voltage range in emergency operation	
3 Control gear suitable for "Joker-Voltage" ?	B2-rectification of the AC voltage (without smoothing)	Pulsating DC voltage 	
4 Control gear compatible with change-over time of the system?	Change-over time: 150 - 1000ms	Typical change-over time of INOTEC systems between mains- and battery operation	
5 Starting behavior of the control gear in AC and DC operation	Stable current consumption within 1.6s	Necessary for individual lamp monitoring (SV). The nominal current of the control gear must be reached within this time if the lamp is intact or defective.	
6 Control gear complies with the standard: (only for fluorescent lamps)	DIN EN 60929	AC and/or DC-supplied electronic control gear for tubular fluorescent lamps - Performance requirements	
7 Control gear complies with the standard: (only for fluorescent lamps)	DIN EN 61347-2-3 (incl. Attachment J)	Particular requirements for AC and/or DC supplied electronic control gear for fluorescent lamps	
8 Control gear complies with the standard: (only for LED)	DIN EN 62384	DC or AC supplied electronic control gear for LED modules - Performance requirements	
9 Control gear complies with the standard: (only for LED)	DIN EN 61347-2-13	Lamp control gear - Part 2-13: Particular requirements for DC or AC supplied electronic control gear for LED modules	
10 Control gear complies with the standard:	DIN EN 55015 (Measurement on AC and DC)	Limits and methods of measurement of radio interference	
11 Control gear complies with the standard:	DIN EN 61000-3-2	Electromagnetic compatibility (EMC) - Part 3-2: Limits - Limits for harmonic current emissions (equipment input current ≤ 16 A per phase)	
12 Control gear complies with the standard:	DIN EN 61547	Equipment for general lighting purposes — EMC immunity requirements	
13 Control gear complies with the DALI-standards:	DIN EN 62386-101 /-102 / -207	The control and status information for monitoring the luminaire is provided via DALI commands. The DALI commands must be 100% compatible.	

Note: VDE 0108 is not a standard for ECG, marking is not applicable

**Technical requirements for electronic control gears for LED and fluorescent luminaires (dimmable or non-dimmable) for operation on INOTEC central battery systems (CPS 220 / CPS FUSION) and emergency power supply systems (NEA)**



**- Technical specifications -**

Manufacturer:	Type / Description:
	Luminaire
	EVG:
Project / Place / Project ID:	LED:
	Specified by:
	Name:
	Company:
	Date:

Features		Explanation	Manufacturer spec.
14	Nominal current of the control gear with connected illuminant in <b>AC- operation (230V)</b>	Selection guide for the calculation of the max. number of luminaires per circuit	mA
15	Nominal current of the control gear with connected illuminant in <b>DC- operation (186V / 216V / 240V)</b>	Selection guide for the calculation of the necessary battery capacity and selection guide for determination of the monitoring module to recognise a normal working lamp correctly.	mA (186V)
			mA (216V)
			mA (240V)
16	Nominal current of the control gear with connected illuminant <b>at set dimming level in DC-operation (186V / 216V / 240V)</b> (for dimmable control gear)	Selection guide for determination of the monitoring module to recognise a normal working lamp correctly.	mA (186V)
			mA (216V)
			mA (240V)
17	Current consumption of the control gear <b>without</b> or with <b>defective</b> illuminant in <b>DC- operation (186V and 240V)</b>	Selection guide for determination of the monitoring module to recognise a lamp failure correctly.	mA (186V)
			mA (240V)
18	Current consumption of the control gear <b>without</b> or with <b>defective</b> illuminant in <b>AC- operation (230V)</b>	Selection guide for determination of the monitoring module to recognise a lamp failure correctly.	mA
19	Dimming level in emergency mode (DC or "Joker") (for dimmable control gear, if activated)	Important for the safety lighting design	%
20	DC detection <b>completely</b> deactivatable ? (for dimmable control gear)	To ensure correct operation, the control gear should not react to a change of the input voltage (DC or "Joker"). In this case, the INOTEC DALI module (DALI-SV module or FMD 230/DALI) controls the control gear.	
21	Max. inrush current of the control gear with connected illuminant in <b>AC- operation (230V)</b>	Important for determining the maximum permissible number of luminaires per circuit in order to take account of the maximum contact load capacity of the circuit changeover circuit or monitoring module.	A / $\mu$ s
22	Use of DALI commands according to IEC 62386 part 102: - DPAC (level) - RECALL MAX LEVEL 0x05 - RECALL MIN LEVEL 0x06 - QUERY STATUS 0x90 - QUERY ACTUAL LEVEL 0xA0 - QUERY LAMP FAILURE 0x92	Control and status information for monitoring the luminaires: - Direct setting of a dimming value - Set maximum level - Set minimum level - Requests status telegram - Requests current dimming value - Requests lamp failure status ( <b>after 2 / 2.5 / 3 seconds!</b> )	

Luminaires, which should work as emergency lighting, have to be in accordance with DIN EN 60598-2-22. (Particular requirements - Luminaires for emergency lighting).

Notes:

For the correctness:

Place, Date

Signature

Manufacturer: OSRAM GmbH Marcel-Breuer Str. 6 D-80807 München	Product:  <b>OTi_DALI_25_220-240_700_NFC_I</b> <b>( 4062172201797 )</b>	<b>OSRAM GmbH</b>
--	--	-------------------

Table 1

Values for load range	Nominal current of the control gear with connected illuminant in AC-operation		Nominal current of the control gear with connected illuminant in DC- operation ( Default output current in emergency mode = 15% )			
	$I_N @ U_N = 230V$ [ mA trms ]	$I_N @ U_N = 240V$ [ mA trms ]	$I_N @ U_N = 186V$ [ mA trms ]	$I_N @ U_N = 216V$ [ mA trms ]	$I_N @ U_N = 240V$ [ mA trms ]	$I_N @ U_N = 260V$ [ mA trms ]
Minimum Load /mA Uout= 11.3 V Iout= 180 mA P= 2 W	31,2	31,9	8,1	7,1	6,6	6,2
Medium Load /mA Uout= 35.4 V Iout= 350 mA P= 12.6 W	70,5	67,8	17,3	15,9	14,5	13,4
Maximum Load /mA Uout= 35.4 V Iout= 700 mA P= 26.2W	132,8	127,5	29,2	26,0	24,0	22,7
Short Load	15,8	16,3	0,5	0,5	0,4	0,4
Open Load	15,7	16,4	0,5	0,5	0,4	0,4

Remarks:

This table shows the currents consumption of the driver at three different operating points (Pmax, Pmed, Pmin) for AC and DC operation.

In DC operation the output current is reduced to 15% light level according to the default parameter setting. This level can be changed via T4T.