

Requirements for dimmable DALI control gears for fluorescent lamps and LED			Version 5
<b>Manufacturer:</b> Inventronics GmbH Berliner Allee 65 86153 Augsburg, Germany	<b>Type / description:</b> ECG-type: OT 75_170-240_1A0 4DIM NFC G3 CE (4062172218993) Date: 04.12.2023		<b>Manufacturer information</b> Complies: YES/NO
<b>Features:</b>	<b>CEAG data:</b>	<b>Explanation:</b>	
Control gear suitable for a DC voltage range:	186V - 260V DC (for Lead-Battery)	Possible voltage range of the battery in emergency mode. (Not for AT-S* Systems required)	Yes
Control gear compatible with the switch-over time of the system?	<b>Switch-over time:</b> 180 ms - 450 ms	Typical switch-over time of CEAG systems between mains supply and emergency power supply	Yes
Starting behavior of the control gear:	<b>Stable current consumption after less than 1.6 sec. maximum.</b>	A stable operation of the control gear after 1.6 seconds of start up is required for the right functionality of the individual monitoring. With max. 20 luminaires for one current circuit: $\Delta I$ in sum < 250 mA are allowed	Yes
Control gear compatible with CEAG STAR-Technology:	<b>Phase-cut telegram (PAT):</b> max. 30 phases (half waves) with max. 60° phase-cuts	During the CEAG STAR switching process, up to 30 half-waves are cut at a maximum of 60°. The control gear must not exhibit any malfunctions such as switching off, flickering	Yes
<u>only for fluorescent lamps:</u> Control gear complies with the standard:	DIN EN 60929	AC and/or DC-supplied electronic control gear for tubular fluorescent lamps - Performance requirements	Not relevant
<u>only for fluorescent lamps:</u> Control gear complies with the standard:	DIN EN 61347-2-3 (incl. Attachment J)	Particular requirements for AC and/or DC supplied electronic control gear for fluorescent lamps	Not relevant
<u>only for LED:</u> Control gear complies with the standard:	DIN EN 62384	DC. Or AC supplied electronic control gear for LED modules - Performance requirements	Yes
<u>only for LED:</u> Control gear complies with the standard:	DIN EN 61347-2-13	Lamp controlgear — Part 2-13: Particular requirements for d. c. or a. c. supplied electronic controlgear for LED modules	Yes
Fullfilled the standard:	DIN EN 55015 (Measurement on AC And DC)	Limits and methods of measurement of radio disturbance characteristics of electrical lighting and similar equipment	Yes
Fullfilled the standard:	DIN EN 61547	Equipment for general lighting purposes — EMC immunity requirements	Yes
Fullfilled the DALI standards:	DIN EN 62386-101 /-102 / -207*	<b>Control gear must have the DALI Logo*</b>	Yes
Note: VDE 0108 is not a standard for ECG, marking is not applicable			
<b>Features:</b>	<b>CEAG-Data:</b>	<b>Explanation:</b>	<b>Manufacturer information:</b>
<u>Important for function test!</u> According to IEC 62386 Part 102 Support of : <b>DALI command 145</b> (Query Control Gear) <b>DALI command 146</b> (Query Lamp Failure)	According to IEC 62386 Part 102	To detect a lamp failure, the V-CG-SB.1 module send DALI command queries (145/146) to the DALI LED driver. These DALI commands are necessary to ensure the lamp failure detection, and must be support by the control gear.	Yes
<u>Important for DC operation:</u> DALI light level	<b>In case of locked DALI light level in DC operation (EOF=Emergency Output Level), the V-CG-SB.1 can not change the light level !</b>	In DC-emergency case the DALI-Light Level is locked to prevent unwanted changes of the luminous flux.	Locked
<u>Important for lighting design:</u> If DALI-Light level is locked, the value of the preset DC-Lightlevel ( in %) is required		Pre-set DC-Light Level e.g. 15% (DALI-value 185 for logarithmic dimming curve)	75%
<b>Note: Important for the planning - Max. no. Of luminaires per circuit</b>			
<u>Important for the contact load SKU:</u> Max. inrush current each converter/luminaire in AC-operation:	Max. permitted inrush current per circuit: SKU 2 x 3A (CG) => 120 A SKU 1 x 6A (CG) => 180 A SKU 4 x 1,5A CG-S => 60 A SKU 2 x 3A CG-S => 250 A SKU 1 x 6A CG-S => 250 A SOU CG-S // S* => 250 A SU S* => 250 A	<b>61A/174us per pcs.</b>  The declaration of the inrush current of the luminaire is important, to calculate the max. possible luminaires on one circuit, to consider the max. contact load limitation of the circuit.	
<b>Luminaires, which are used for emergency lighting, must be according to the standard DIN EN 60598-2-22 (particular requirements - Luminaires for emergency lighting)</b>			
*Control of V-CG-SB.1 to the DALI LED driver is 100% done via DALI-commands according to IEC 62386-101 /-102 so the DALI LED driver must sign with the DALI logo			
<b>Max. 1 DALI- Driver to wire with 1 V-CG-SB.1</b> In use of manifold ballasts, the different lamp failure detection of the manufacturer must be consider! Some devices don't detect a failure if one lamp is defect.			

*Philip Gie*

Manufacturer: Inventronics GmbH Berliner Allee 65 86153 Augsburg, Germany <a href="http://www.inventronicsglobal.com">www.inventronicsglobal.com</a>	Product:  <p style="text-align: center;"><b>OT 75_170-240_1A0 4DIM NFC G3 CE (AM41131)</b></p>	<b>Inventronics GmbH</b>
--	--	--------------------------

Table 1

Values for load range	AC-operation			DC-Operation (For DALI Devices @ default DC Dim level e.g. 15%)			
	230VAC/50Hz Itrms_in ( mA )	240VAC/50Hz Itrms_in ( mA )	264VAC/50Hz Itrms_in ( mA )	186VDC Idc_in ( mA )	216VDC Idc_in ( mA )	240VDC Idc_in ( mA )	260VDC Idc_in ( mA )
Min. Load /mA Uout= 50 V Iout= 150 mA	70.4	68.7	71.6	54.6	48.2	44.2	41.7
	PF: 0.5863	PF: 0.5674	PF: 0.493	PF: NA	PF: NA	PF: NA	PF: NA
Mid. Load /mA Uout= 107 V Iout= 350 mA	182.0	175.8	164.3	217.3	186.7	167.3	154.9
	PF: 0.96	PF: 0.952	PF: 0.9256	PF: NA	PF: NA	PF: NA	PF: NA
Max. Load /mA Uout= 107 V Iout= 700 mA	356.7	341.0	311.4	333.4	286.2	257.8	237.3
	PF: 0.9922	PF: 0.9901	PF: 0.984	PF: NA	PF: NA	PF: NA	PF: NA
Short/Open Load	47.1	48.5	51.7	25.8	24.2	23.5	22.9
	PF: 0.02	PF: 0.018	PF: 0.016	PF: NA	PF: NA	PF: NA	PF: NA

**Remarks:**

- 1.) This table shows the currents consumption of the driver at three different operating points (Pmax, Pmid, Pmin) for AC and DC operation.
- 2.) This table is intended for rough design decisions . It is not a replacement for individual functional measurements!