


Technical requirements for electronic control gears for LED and fluorescent luminaires (dimmable or non-dimmable) for operation on INOTEC central battery systems (CPS 220 / CPS FUSION) and emergency power supply systems (NEA)

- General requirements -

Manufacturer:	Type / Description:
	Luminaire
	EVG: OTi DALI 10/220-240/700 NFC (AM29184)
Project / Place / Project ID:	LED:
	Specified by:
	Name: Dr. K.Schmidtman
	Company: OSRAM GmbH
	Date: 14.05.2020

Features	Techn. data / INOTEC requirements	Explanation	Fulfilled (Yes / No)
1 Voltage range AC	230V ± 10%	Voltage range in normal mains operation	Yes
2 Voltage range DC	186V - 260V	Possible voltage range in emergency operation	Yes
3 Control gear suitable for "Joker-Voltage" ?	B2-rectification of the AC voltage (without smoothing)	Pulsating DC voltage 	Yes
4 Control gear compatible with change-over time of the system?	Change-over time: 150 - 1000ms	Typical change-over time of INOTEC systems between mains- and battery operation	Yes
5 Starting behavior of the control gear in AC and DC operation	Stable current consumption within 1.6s	Necessary for individual lamp monitoring (SV). The nominal current of the control gear must be reached within this time if the lamp is intact or defective.	Yes
6 Control gear complies with the standard: (only for fluorescent lamps)	DIN EN 60929	AC and/or DC-supplied electronic control gear for tubular fluorescent lamps - Performance requirements	Not relevant
7 Control gear complies with the standard: (only for fluorescent lamps)	DIN EN 61347-2-3 (incl. Attachment J)	Particular requirements for AC and/or DC supplied electronic control gear for fluorescent lamps	Not relevant
8 Control gear complies with the standard: (only for LED)	DIN EN 62384	DC or AC supplied electronic control gear for LED modules - Performance requirements	Yes
9 Control gear complies with the standard: (only for LED)	DIN EN 61347-2-13	Lamp control gear - Part 2-13: Particular requirements for DC or AC supplied electronic control gear for LED modules	Yes
10 Control gear complies with the standard:	DIN EN 55015 (Measurement on AC and DC)	Limits and methods of measurement of radio interference	Yes
11 Control gear complies with the standard:	DIN EN 61000-3-2	Electromagnetic compatibility (EMC) - Part 3-2: Limits - Limits for harmonic current emissions (equipment input current ≤ 16 A per phase)	Yes
12 Control gear complies with the standard:	DIN EN 61547	Equipment for general lighting purposes — EMC immunity requirements	Yes
13 Control gear complies with the DALI-standards:	DIN EN 62386-101 /-102 / -207	The control and status information for monitoring the luminaire is provided via DALI commands. The DALI commands must be 100% compatible.	Yes

Note: VDE 0108 is not a standard for ECG, marking is not applicable

Technical requirements for electronic control gears for LED and fluorescent luminaires (dimmable or non-dimmable) for operation on INOTEC central battery systems (CPS 220 / CPS FUSION) and emergency power supply systems (NEA)



- Technical specifications -

Manufacturer:	Type / Description:
	Luminaire
	EVG: OTi DALI 10/220-240/700 NFC (AM29184)
Project / Place / Project ID:	LED:
	Specified by:
	Name: Dr. K.Schmidtman
	Company OSRAM GmbH
	Date: 14.05.2020

Features		Explanation	Manufacturer spec.
14	Nominal current of the control gear with connected illuminant in AC- operation (230V)	Selection guide for the calculation of the max. number of luminaires per circuit	Table 1 mA
15	Nominal current of the control gear with connected illuminant in DC- operation (186V / 216V / 240V)	Selection guide for the calculation of the necessary battery capacity and selection guide for determination of the monitoring module to recognise a normal working lamp correctly.	Table 1 mA (186V)
			-" mA (216V)
			-" mA (240V)
16	Nominal current of the control gear with connected illuminant at set dimming level in DC-operation (186V / 216V / 240V) (for dimmable control gear)	Selection guide for determination of the monitoring module to recognise a normal working lamp correctly.	- mA (186V)
			- mA (216V)
			- mA (240V)
17	Current consumption of the control gear without or with defective illuminant in DC- operation (186V and 240V)	Selection guide for determination of the monitoring module to recognise a lamp failure correctly.	Table 1 mA (186V)
			-" mA (240V)
18	Current consumption of the control gear without or with defective illuminant in AC- operation (230V)	Selection guide for determination of the monitoring module to recognise a lamp failure correctly.	Table 1 mA
19	Dimming level in emergency mode (DC or "Joker") (for dimmable control gear, if activated)	Important for the safety lighting design	15 (*1) %
20	DC detection completely deactivable ? (for dimmable control gear)	To ensure correct operation, the control gear should not react to a change of the input voltage (DC or "Joker"). In this case, the INOTEC DALI module (DALI-SV module or FMD 230/DALI) controls the control gear.	Yes
21	Max. inrush current of the control gear with connected illuminant in AC- operation (230V)	Important for determining the maximum permissible number of luminaires per circuit in order to take account of the maximum contact load capacity of the circuit changeover circuit or monitoring module.	5 / 100 A / µs
22	Use of DALI commands according to IEC 62386 part 102: - DPAC (level) - RECALL MAX LEVEL 0x05 - RECALL MIN LEVEL 0x06 - QUERY STATUS 0x90 - QUERY ACTUAL LEVEL 0xA0 - QUERY LAMP FAILURE 0x92	Control and status information for monitoring the luminaires: - Direct setting of a dimming value - Set maximum level - Set minimum level - Requests status telegram - Requests current dimming value - Requests lamp failure status (after 2 / 2.5 / 3 seconds!)	Yes

Luminaires, which should work as emergency lighting, have to be in accordance with DIN EN 60598-2-22. (Particular requirements - Luminaires for emergency lighting).

Notes:

*1) The DC output level is locked to 15% as preset factory setting. *2) Not to be used in high risk areas, special release required. >>>This LED driver declaration does not substitute a system test and release in a specific installation.<<<

For the correctness:

Garching, 14.05.2020

Place, Date

Dr. Schmidtman DS QM LAB&SQM
Bernhard Schönmel

Signature

Manufacturer: OSRAM GmbH Marcel-Breuer Str. 6 D-80807 München	Product: OTi DALI 10/220-240/700 NFC (AM29184)	OSRAM GmbH
--	---	-------------------

Table 1

Values for load range	Nominal current of the control gear with connected illuminant in AC-operation		Nominal current of the control gear with connected illuminant in DC- operation (Default output current in emergency mode = 15%)			
	$I_N @ U_N = 230V$ [mA trms]	$I_N @ U_N = 240V$ [mA trms]	$I_N @ U_N = 186V$ [mA trms]	$I_N @ U_N = 216V$ [mA trms]	$I_N @ U_N = 240V$ [mA trms]	$I_N @ U_N = 260V$ [mA trms]
Minimum Load /mA Uout= 10 V Iout= 150 mA P= 1,5 W	28	28	24	22	20	19
Medium Load /mA Uout= 14 V Iout= 315 mA P= 4,4 W	38	37	24	23	21	20
Maximum Load /mA Uout= 14 V Iout= 700 mA P= 10 W	60	58	29	26	23	22
Open Load /mA	22	21	23	21	20	19
Short Load /mA	22	21	23	21	20	19

Remarks:

This table shows the currents consumption of the driver at three different operating points (Pmax, Pmed, Pmin) for AC and DC operation.
 In DC operation the output current is reduced to 15% light level according to the default parameter setting. This level can be changed via T4T.