

## Requirements for dimmable DALI control gears for fluorescent lamps and LED

**Version 0**

<b>Manufacturer:</b> Osram GmbH Marcel-Breuer-Straße 6 D-80807 München	<b>Type / description:</b>  ECG-type: Oti DALI 50/220-240/1A4 LT2 FAN (ident code: AB42878)		
<b>Features:</b>	<b>CEAG data:</b>	<b>Comment:</b>	<b>Complies: (Yes/No)</b>
Control gear suitable for a DC voltage range:	<b>186V - 260V DC (for Lead-Battery) 186V - 275V DC (for NiCD-Battery)</b>	Possible voltage range of the battery in emergency mode. (Not for AT-S <sup>+</sup> Systems required)	Yes
Control gear compatible with the switch-over time of the system?	<b>Switch-over time: 180 ms - 450 ms</b>	Typical switch-over time of CEAG systems between mains supply and emergency power supply	Yes
Starting behavior of the control gear:	<b>Stable current consumption after less than 1.6 sec. maximum.</b>	Necessary for an individual monitoring. $\Delta I < 12,5 \text{ mA}$ per luminaire, with max. 20 luminaires per circuit $\Delta I \text{ sum} < 250 \text{ mA}$	Yes
<u>only for fluorescent lamps:</u> Control gear complies with the standard:	<b>DIN EN 60929</b>	AC and/or DC-supplied electronic control gear for tubular fluorescent lamps - Performance requirements	not relevant
<u>only for fluorescent lamps:</u> Control gear complies with the standard:	<b>DIN EN 61347-2-3 (incl. Attachment J)</b>	Particular requirements for AC and/or DC supplied electronic control gear for fluorescent lamps	not relevant
<u>only for LED:</u> Control gear complies with the standard:	<b>DIN EN 62384</b>	DC. Or AC supplied electronic control gear for LED modules - Performance requirements	Yes
<u>only for LED:</u> Control gear complies with the standard:	<b>DIN EN 61347-2-13</b>	Lamp controlgear — Part 2-13: Particular requirements for d. c. or a. c. supplied electronic controlgear for LED modules	Yes
Fullfilled the standard:	<b>DIN EN 55015 (Measurement on AC And DC)</b>	Limits and methods of measurement of radio disturbance characteristics of electrical lighting and similar equipment	Yes
Fullfilled the standard:	<b>DIN EN 61000-3-2</b>	Electromagnetic compatibility (EMC) — Part 3-2: Limits — Limits for harmonic current emissions (equipment input current $\leq 16 \text{ A}$ per phase)	Yes
Fullfilled the standard:	<b>DIN EN 61547</b>	Equipment for general lighting purposes — EMC immunity requirements	Yes (*3)
Fullfilled the DALI standards:	<b>DIN EN 62386-101 /-102 / -207</b>	<b>Control gear must have the DALI Logo (*1)</b>	Yes
<small>Note: VDE 0108 is not a standard for ECG, marking is not applicable</small>			
<b>Features:</b>	<b>CEAG-Data:</b>	<b>Comment:</b>	<b>Manufacturer's instructions:</b>
<u>Important for function test!</u> According to IEC 62386 Part 102 Support of : <b>DALI command 145 (Query Control Gear) DALI command 146 (Query Lamp Failure)</b>	<b>According to IEC 62386 Part 102</b>	To detect a lamp failure, the V-CG-SB.1 module send DALI command queries (145/146) to the DALI LED driver	Yes
<u>Important for DC light output:</u> Behavior in DC operation: - <b>Unlocked DC light output level</b> - <b>Locked DC light output level</b>	<b>DC light output settings on V-CG-SB.1 only active if control gear is unlocked!</b>	<b>In case of locked DC light output level, the DC level of V-CG-SB.1 is not active !</b>	<b>Unlocked DC [ ] Locked DC [ x ]</b>
<u>Important for lighting design:</u> If locked DC light output the lightout level in % is required	<b>No control of light output level from V-CG-SB.1 in DC operation possible!</b>	Locked light output level in %, e.g. 15% (*2)	<b>15%</b>
<u>Important for the contact load SKU:</u> Max. inrush current each converter/luminaire in AC-operation:	<b>Max. permitted inrush current per circuit: SKU 2 x 3A (CG) =&gt; 120 A SKU 1 x 6A (CG) =&gt; 180 A SKU 4 x 1,5A CG-S =&gt; 60 A SKU 2 x 3A CG-S =&gt; 250 A SKU 1 x 6A CG-S =&gt; 250 A SOU CG-S // S<sup>+</sup> =&gt; 250 A SU S<sup>+</sup> =&gt; 250 A</b>	Describes the max. inrush current of all ballasts in a circuit, to calculate the maximum contact rating of the circuit.	<b>Ip=20A / Th=194µs</b>
<u>Important for lighting design:</u> Luminous flux ratio: DC-operation at 186 V in comparison to 230 V AC operation	-	Light output in battery operation of the ballast, for the light calculation (*2)	<b>15%</b>

**Luminaires, which are used for emergency lighting, must be according to the standard DIN EN 60598-2-22 (particular requirements - Luminaires for emergency lighting)**

\*1: Control of V-CG-SB.1 to the DALI LED driver is 100% done via DALI-commands according to IEC 62386-101 /-102 so the DALI LED driver must sign with the DALI logo

\*2: The DC Output Level is locked in DC Mode to 15%, it is possible to unlock with DALI magic and Tuner 4 Tronic

\*3: Not to be used in high risk areas, special release required

**Max. 1 DALI-Driver to wire with 1 V-CG-SB.1**

In use of manifold ballasts, the different lamp failure detection of the manufacturer must be consider! Some devices don't detect a failure if one lamp is defect.

Date: 03.Feb.2017

Requirements for electronic non-dimmable  
control gears for fluorescent lamps and LED



Manufacturer:  
OSRAM GmbH  
Marcel-Breuer Str. 6  
D-80807 München

Product

Oti DALI 50/220-240/1A4 LT2 FAN

**OSRAM**

LED controller type	Values for load range	I <sub>n</sub> in AC- operation (230V) / mA (trms)	I <sub>n</sub> in AC- operation (240V) / mA (trms)	I <sub>n</sub> in DC- operation (186V) / mA (trms)	I <sub>n</sub> in DC- operation (216V) / mA (trms)	I <sub>n</sub> in DC- operation (240V) / mA (trms)	I <sub>n</sub> in DC- operation (260V) / mA (trms)
Oti DALI 50/220-240/1A4 LT2 FAN	U <sub>min</sub> , I <sub>min</sub>	97,43	96,10	19,11	16,57	15,28	14,24
	U <sub>min</sub> , I <sub>max</sub>	136,96	125,50	26,81	23,13	21,28	20,14
	U <sub>max</sub> , I <sub>min</sub>	212,14	204,29	40,38	35,03	31,89	29,97
	U <sub>max</sub> , I <sub>max</sub>	273,06	262,16	65,27	56,14	50,84	47,37
	Open Load	57,57	59,78	47,88	45,19	42,94	40,98
	Short Load	57,62	59,80	47,89	45,20	42,95	40,99

Maximum inrush current for ECG in AC Operation

I<sub>peak</sub>= 20 A  
T<sub>H</sub>= 194 μs