

Requirements for electronic non-dimmable control gears for fluorescent lamps and LED			Version 14
Manufacturer: OSRAM GmbH Marcel-Breuer-Str. 6 D-80807 München	Type / description: ECG-type: OT 110 /170...240/1A0 4DIM LT2 G2 CE (4052899981959) Date: 12.05.2022		Manufacturer information Complies: YES/NO
Specifications:	CEAG data:	Explanation:	
Control gear suitable for a DC voltage range:	186V - 260V DC (for Lead-Battery)	Possible voltage range of the battery in emergency mode. (Not for AT-S+ Systems required)	Yes
Control gear compatible with the switch-over time of the system?	Switch-over time: 180 ms - 450 ms	Typical switch-over time of CEAG systems between mains supply and emergency power supply	Yes
Starting behavior of the control gear:	Stable current consumption after less than 1.6 sec. maximum.	A stable operation of the control gear after 1.6 seconds of start up is required for the right functionality of the individual monitoring. With max. 20 luminaires for one current circuit: ΔI in sum < 250 mA are allowed	Yes
Control gear compatible with CEAG STAR-Technology:	Phase-cut telegram (PAT): max. 30 phases (half waves) with max. 60° phase-cuts	During the CEAG STAR switching process, up to 30 half-waves are cut at a maximum of 60°. The control gear must not exhibit any malfunctions such as switching off, flickering	Yes
only for fluorescent lamps: Control gear complies with the standard:	DIN EN 60929	AC and/or DC-supplied electronic control gear for tubular fluorescent lamps - Performance requirements	Not relevant
only for fluorescent lamps: Control gear complies with the standard:	DIN EN 61347-2-3 (incl. Attachment J)	Particular requirements for AC and/or DC supplied electronic control gear for fluorescent lamps	Not relevant
only for LED: Control gear complies with the standard:	DIN EN 62384	AC or DC supplied electronic control gear for LED modules - Performance requirements	Yes
only for LED: Control gear complies with the standard:	DIN EN 61347-2-13	Particular requirements for AC or DC supplied electronic control gear for LED modules	Yes
Control gear complies with the standard:	DIN EN 55015 (Measured in AC and DC)	Limits and methods of measurement of radio disturbance characteristics of electrical lighting and similar equipment	Yes
Control gear complies with the standard:	DIN EN 61000-3-2, Pkt. 7.3 a.)	see *Important note!	Yes
Control gear complies with the standard:	DIN EN 61547	Equipment for general lighting purposes - EMC immunity requirements	Yes
Note: The labeling "according to VDE 0108" is not meaningful, because this is not a control gear standard!			
Specifications:	CEAG data:	Explanation:	Manufacturer information:
<u>Important for functiontest:</u> Voltage-dependent Input current of the control gear incl. LED in DC and AC operation:	V-CG-S2: >9,4 mA or >12,7 mA = OK V-CG-S: >16 mA or >47 mA = OK V-CG-SE: >16 mA or >47 mA = OK V-CG-SUW: >47 mA = OK CG-K: >16 mA or >47 mA = OK	Minimum current of the LED driver with LED module to GOOD detection via the monitoring module. In the voltage range of 189 - 264V AC on AT-S+ or 186 - 260V DC on ZB-S/LP-STAR the input current must be higher than the specified current values. see *Important note!	AC: see Table (AT-S+) DC: see Table (ZB-S/ LP-STAR)
<u>Important for functiontest:</u> Voltage-dependent No-load current of the control gear (without or defect LED module) in DC and AC - operation*:	V-CG-S2: <5,8 mA or <7,9 mA = n.OK V-CG-S: <10 mA or <28 mA = n.OK V-CG-SE: <10 mA or <28 mA = n.OK V-CG-SUW: <28 mA = n.OK CG-K: <10 mA or <28 mA = n.OK	Maximal current of the LED driver with LED module for BAD detection via the monitoring module. In the voltage range of 189 - 264V AC on AT-S+ or 186 - 260V DC on ZB-S/LP-STAR the input current must be lower than the specified current values. see *Important note!	AC: see Table (AT-S+) DC: see Table (ZB-S/ LP-STAR)
Important for the power consumption of addressable ballast:	V-CG-S2 = 30 A V-CG-S = 30 A V-CG-SE = 30 A V-CG-SUW = 80 A CG-K = 30 A	The max. inrush current of each monitoring module has to be considered!	AC: see Table (AT-S+) DC: see Table (ZB-S/ LP-STAR)
Note: Important for the planning - Max. no. Of luminaires per circuit			
<u>Important for the contact load SKU:</u> Max. inrush current of each luminaire in AC operation	Max. permitted inrush current per circuit: SKU 2 x 3A (CG) => 120 A SKU 1 x 6A (CG) => 180 A SKU 4 x 1,5A CG-S => 60 A SKU 2 x 3A CG-S => 250 A SKU 1 x 6A CG-S => 250 A SOU CG-S // S* => 250 A SU S* => 250 A	<p style="text-align: center;">I-peak=65A Th=160µs per pcs.</p> <p>The declaration of the inrush current of the luminaire is important, to calculate the max. possible luminaires on one circuit, to consider the max. contact load limitation of the circuit.</p>	
Luminaires for emergency lighting must comply with DIN EN 60598-2-22 (Particular requirements -Luminaires for emergency lighting) *Important note! For AT-S+ systems and for battery systems (ZB-S / LP-STAR) with active preliminary time for AC about 300 seconds (EOL detection of T5 lamps) for the function test, the current consumption must be sinusoidal, t.m. all control gears (<25W as well) must have an active PFC (Power Factor Correction)! See DIN EN 61000-3-2, Pkt. 7.3 a.) Note EOL (End of Life) detection (T5 > 14Watt): The AC preliminary time is valid for the complete system (e.g. ZB-S), not possible for individual circuits. The modules of the V-CG-S series monitor the current consumption on the primary side of the control gear for LED modules within the specified limits. Failures of individual LEDs (low-impedance) on the secondary side do not inevitably lead to a modification of current consumption on the primary side, and in such cases cannot be detected as a failure.			
06. Mrz 21			