


Requirements for dimmable DALI control gears for fluorescent lamps and LED			Version 5
Manufacturer: OSRAM GmbH Marcel-Breuer-Str. 6 D-80807 München	Type / description: ECG-type: OT 200/170-240/1A0 4DIM NFC G3 (AM41085) (4062172219105) Date: 03.02.2022		Manufacturer information Complies: YES/NO
Features:	CEAG data:	Explanation:	
Control gear suitable for a DC voltage range:	186V - 260V DC (for Lead-Battery)	Possible voltage range of the battery in emergency mode. (Not for AT-S* Systems required)	Yes
Control gear compatible with the switch-over time of the system?	Switch-over time: 180 ms - 450 ms	Typical switch-over time of CEAG systems between mains supply and emergency power supply	Yes
Starting behavior of the control gear:	Stable current consumption after less than 1.6 sec. maximum.	A stable operation of the control gear after 1.6 seconds of start up is required for the right functionality of the individual monitoring. With max. 20 luminaires for one current circuit: ΔI in sum < 250 mA are allowed	Yes
Control gear compatible with CEAG STAR-Technology:	Phase-cut telegram (PAT): max. 30 phases (half waves) with max. 60° phase-cuts	During the CEAG STAR switching process, up to 30 half-waves are cut at a maximum of 60°. The control gear must not exhibit any malfunctions such as switching off, flickering	Yes
<u>only for fluorescent lamps:</u> Control gear complies with the standard:	DIN EN 60929	AC and/or DC-supplied electronic control gear for tubular fluorescent lamps - Performance requirements	Not relevant
<u>only for fluorescent lamps:</u> Control gear complies with the standard:	DIN EN 61347-2-3 (incl. Attachment J)	Particular requirements for AC and/or DC supplied electronic control gear for fluorescent lamps	Not relevant
<u>only for LED:</u> Control gear complies with the standard:	DIN EN 62384	DC. Or AC supplied electronic control gear for LED modules - Performance requirements	Yes
<u>only for LED:</u> Control gear complies with the standard:	DIN EN 61347-2-13	Lamp controlgear — Part 2-13: Particular requirements for d. c. or a. c. supplied electronic controlgear for LED modules	Yes
Fullfilled the standard:	DIN EN 55015 (Measurement on AC And DC)	Limits and methods of measurement of radio disturbance characteristics of electrical lighting and similar equipment	Yes
Fullfilled the standard:	DIN EN 61547	Equipment for general lighting purposes — EMC immunity requirements	Yes
Fullfilled the DALI standards:	DIN EN 62386-101 /-102 / -207*	Control gear must have the DALI Logo*	Yes
Note: VDE 0108 is not a standard for ECG, marking is not applicable			
Features:	CEAG-Data:	Explanation:	Manufacturer information:
<u>Important for function test!</u> According to IEC 62386 Part 102 Support of : DALI command 145 (Query Control Gear) DALI command 146 (Query Lamp Failure)	According to IEC 62386 Part 102	To detect a lamp failure, the V-CG-SB.1 module send DALI command queries (145/146) to the DALI LED driver. These DALI commands are necessary to ensure the lamp failure detection, and must be support by the control gear.	Yes
<u>Important for DC operation:</u> DALI light level	In case of locked DALI light level in DC operation (EOF=Emergency Output Level), the V-CG-SB.1 can not change the light level !	In DC-emergency case the DALI-Light Level is locked to prevent unwanted changes of the luminous flux.	Not Locked
<u>Important for lighting design:</u> If DALI-Light level is locked, the value of the preset DC-Lightlevel (in %) is required		Pre-set DC-Light Level e.g. 15% (DALI-value 185 for logarithmic dimming curve)	(*1) 100%
Note: Important for the planning - Max. no. Of luminaires per circuit			
<u>Important for the contact load SKU:</u> Max. inrush current each converter/luminaire in AC-operation:	Max. permitted inrush current per circuit: SKU 2 x 3A (CG) => 120 A SKU 1 x 6A (CG) => 180 A SKU 4 x 1,5A CG-S => 60 A SKU 2 x 3A CG-S => 250 A SKU 1 x 6A CG-S => 250 A SOU CG-S // S* => 250 A SU S* => 250 A	83A/222us per pcs. The declaration of the inrush current of the luminaire is important, to calculate the max. possible luminaires on one circuit, to consider the max. contact load limitation of the circuit.	
Luminaires, which are used for emergency lighting, must be according to the standard DIN EN 60598-2-22 (particular requirements - Luminaires for emergency lighting)			
*Control of V-CG-SB.1 to the DALI LED driver is 100% done via DALI-commands according to IEC 62386-101 /-102 so the DALI LED driver must sign with the DALI logo (*1) Emergency feature is disable and factory setting is 100% of the Dali light level. In DC mode at the 100% of Dali light level, the output current is limited. It is possible enable Emergency feature with DALI magic and Tuner 4 Tronic			
Max. 1 DALI- Driver to wire with 1 V-CG-SB.1 In use of manifold ballasts, the different lamp failure detection of the manufacturer must be consider! Some devices don't detect a failure if one lamp is defect.			

02.August.2023


Technical requirements for dimmable DALI control gears
for fluorescent lamps and LED



Manufacturer: OSRAM GmbH Marcel-Breuer Str. 6 D-80807 München	Product: OT 200/170-240/1A0 4DIM NFC G3 CE	OSRAM GmbH
--	--	-------------------

Table 1

LED controller type	Values for load range	IN in AC-operation (230V) / mA (trms)	IN in AC-operation (240V) / mA (trms)	IN in DC-operation (186V) / mA (trms)	IN in DC-operation (216V) / mA (trms)	IN in DC-operation (240V) / mA (trms)	IN in DC-operation (260V) / mA (trms)
OT 200/170-240/1A0 4DIM NFC G3 CE	Maximum Load /mA Uout= 140 V Iout= 150 mA	150	150	134	116	105	97
	Medium Load /mA Uout= 190 V Iout= 525 mA	478	455	602	498	451	412
	Minimum Load /mA Uout= 190 V Iout= 1050 mA	932	890	895	743	667	615
	No Load	83	87	4,7	5,7	6,7	15,8
	Short Load	83	87	4,8	5,5	5,9	14,9

Maximum inrush current for ECG in AC Operation: Ipeak = 83 A TH = 222.5 μs

Deniele Lucato