


Technical requirements for electronic control gears for LED- / fluorescent- luminaires for connection at INOTEC central battery systems

Manufacturer: OSRAM GmbH Marcel-Breuer-Str. 6 D-80807 München	Type / Description:
	Luminaire: EVG: OT FIT 150/220-240/1A0 D NFC IND L (ident code: AM15161)
	LED:
Project / Place / Project ID:	Specified by: Name: R.Brazinskas
	Company: OSRAM GmbH
	Date: 23.11.2018

Features	Techn. data / INOTEC requirements	Explanation	Fulfilled (Yes / No)
1 Voltage range AC	230V ± 10%	Voltage range in normal mains operation	Yes
2 Voltage range DC	186V - 260V	Possible voltage range in emergency operation	Yes
3 Control gear suitable for "Joker-Voltage" ?	B2-rectification of the AC voltage (without smoothing)	Pulsating DC voltage 	Yes
4 Control gear compatible with change-over time of the system?	Change-over time: 150 - 1000ms	Typical change-over time of INOTEC systems between mains- and battery operation	Yes
5 Starting behavior of the control gear in DC operation	Stable current consumption within 3s	Necessary for individual lamp monitoring (SV)	Yes
6 Control gear complies with the standard: (only for fluorescent lamps)	DIN EN 60929	AC and/or DC-supplied electronic control gear for tubular fluorescent lamps - Performance requirements	Not relevant
7 Control gear complies with the standard: (only for fluorescent lamps)	DIN EN 61347-2-3 (incl. Attachment J)	Particular requirements for AC and/or DC supplied electronic control gear for fluorescent lamps	Not relevant
8 Control gear complies with the standard: (only for LED)	DIN EN 62384	DC or AC supplied electronic control gear for LED modules - Performance requirements	Yes
9 Control gear complies with the standard: (only for LED)	DIN EN 61347-2-13	Lamp control gear - Part 2-13: Particular requirements for DC or AC supplied electronic control gear for LED modules	Yes
10 Control gear complies with the standard:	DIN EN 55015 (Measurement on AC and DC)	Limits and methods of measurement of radio interference	Yes
11 Control gear complies with the standard:	DIN EN 61000-3-2	Electromagnetic compatibility (EMC) - Part 3-2: Limits - Limits for harmonic current emissions (equipment input current ≤ 16 A per phase)	Yes
12 Control gear complies with the standard:	DIN EN 61547	Equipment for general lighting purposes — EMC immunity requirements	(*2)Yes

Note: VDE 0108 is not a standard for ECG, marking is not applicable

Technical requirements for electronic control gears for LED- / fluorescent- luminaires for connection at INOTEC central battery systems



Manufacturer: OSRAM GmbH Marcel-Breuer-Str. 6 D-80807 München	Type / Description:
	Luminaire: EVG: OT FIT 150/220-240/1A0 D NFC IND L (ident code: AM15161)
	LED:
Project / Place / Project ID:	Specified by: Name: R.Brazinskis
	Company: OSRAM GmbH
	Date: 23.11.2018

Features	Techn. data / INOTEC requirements	Explanation	Manufacturer information
13 Nominal current of the control gear with connected illuminant in AC- operation (230V)		Selection guide for the calculation of the max. number of luminaires per circuit	See Table1
14 Nominal current of the control gear with connected illuminant in DC- operation (216V)		Selection guide for the calculation of the necessary battery capacity	See Table1
15 Nominal current of the control gear with connected illuminant in DC- operation (186V und 260V) and pre-set luminous flux	J-SV-Modul/S (5-120W): > 20mA = OK J-SV-Modul.2/S (20-300W): > 70mA = OK J-SV-Modul.3/S (2-30W): > 12mA = OK J-SV-Modul.4/S (18-120W): > 70mA = OK J-SV-Modul.L/S (20-120W): > 20mA = OK J-SV-Modul T/S (20-100W): > 60mA = OK	Selection guide for determination of the monitoring module: The values are not to be undercut within the voltage range 186VDC - 260VDC to recognise a normal working lamp correctly.	See Table1
			See Table1
16 Luminous flux in DC- operation (186V)		Important for the safety lighting design	100%
17 Standby current of the control gear with no illuminant connected or with defective illuminant in DC-operation (186V and 260V)	J-SV-Modul/S (5-120W): < 10mA = n.OK J-SV-Modul.2/S (20-300W): < 45mA = n.OK J-SV-Modul.3/S (2-30W): < 8mA = n.OK J-SV-Modul.4/S (18-120W): < 45mA = n.OK J-SV-Modul.L/S (20-120W): < 10mA = n.OK J-SV-Modul T/S (20-100W): < 50mA = n.OK	Selection guide for determination of the monitoring module: The values are not to be exceeded within the voltage range 186VDC - 260VDC to recognise a lamp failure correctly.	See Table1 (*1)
18 Max. inrush current of the control gear with connected lamp in AC operation (230V)	Max. permitted inrush current per circuit / monitoring module: SK 4x2A: 250A / 500µs SK 2x4A: 250A / 500µs SK 2x3A: 250A / 500µs SK 1x6A: 250A / 500µs J-SV-Modul T/S: 40A / 500µs all other J-SV-modules: 80A / 500µs	Describes the max. inrush current of all ballasts in a circuit, to calculate the maximum contact rating of the circuit	I _{peak} =5A TH=1.7 ms (*3)

Luminaires, which should work as emergency lighting, have to be in accordance with DIN EN 60598-2-22. (Particular requirements - Luminaires for emergency lighting).

(*1): The J-SV-monitoring modules monitor the current consumption on the primary side of the control gear for LED modules within the specified limits. Failures of individual LEDs (low-impedance) on the secondary side do not inevitably lead to a modification of current consumption on the primary side, and in such cases cannot be detected as a failure.

(*2): Not to be used in high risk areas, special release required

(*3): For calculation the inrush current of the monitoring module must be taken into consideration!

Notes:

For the correctness:

J. Proch
28.11.2018

Place, Date

DS D SST
Dr. Kay Schmidt
DS QM LAB&SQM
Kermit Schmal

Signature

Technical requirements for electronic control gears for
LED- / fluorescent- luminaires for connection at INOTEC
central battery systems



Manufacturer: OSRAM GmbH Marcel-Breuer Str. 6 D-80807 München	Product: OT FIT 150/220-240/1A0 D NFC IND L	
--	---	--

Table 1

LED controller type	Values for load range	I_M in AC-operation (230V) / mA (trms)	I_M in AC- operation (240V) / mA (trms)	I_M in DC-operation (186V) / mA (trms)	I_M in DC- operation (216V) / mA (trms)	I_M in DC- operation (240V) / mA (trms)	I_M in DC- operation (260V) / mA (trms)
OT FIT 150/220-240/1A0 D NFC IND L	Maximum Load /mA $U_{out} = 200V$ $I_{out} = 750mA$	714	684	897	763	680	625
	Medium Load /mA $U_{out} = 150V$ $I_{out} = 500mA$	367	354	443	380	341	315
	Minimum Load /mA $U_{out} = 100V$ $I_{out} = 430mA$	231	224	263	228	208	195
	No Load	62	64	10	10	8	10
	Short Load	67	66	6	12	13	20

Maximum inrush current for ECG in AC Operation:

$I_{peak} = 5A$

$T_H = 1,7ms$